

Getting Started

Proper labelling and packaging of batteries is extremely important when shipping thru the mail.

Before using any LampMaster battery recycling kit, ensure that you check the chemistries of all batteries.

If the chemistry requires, tape the terminals when instructed using **CLEAR TAPE ONLY**

Acceptable Batteries

- Alkaline
- Nickel Cadmium / Nickel Metal Hydride
- Zinc Air or Zinc Carbon
- Non-lithium Button Cell
- Lithium Ion (Rechargeable)*
- Nonspillable Sealed Lead Acid*

NO WET CELL BATTERIES

NO LITHIUM METAL (PRIMARY) BATTERIES IN THE DRY CELL BATTERY KIT

**Additional labels included*

Certificates of Recycling

- Upon receipt of each recycling kit, a link to download a certificate of recycling will be emailed to the account holder.
- Certificates are always available online: My Account > View Certificates

Collecting Batteries In Provided Pails

- Fill out the **GENERATOR** and **ACCUMULATION START DATE** information on the date that you start filling the pail with batteries.
- Fill the pail with batteries. Be sure to follow terminal taping instructions below.
- After the pail is full, securely attach the lid to the pail.
- For ½ or 1gal kits, return to original shipping box, seal with packing tape, and attach FedEx return label along with any additional necessary labels (included) according to instructions below.
- For 2.5 or 5gal kits, confirm FedEx return label is attached to outside of pail and attach any additional necessary labels (included) according to instructions below.
- If the battery kit contains any lithium batteries, the maximum gross weight (including packaging) allowed is 66 pounds.

Taping Terminals On Batteries

- Lithium-Ion Batteries (if terminals are exposed)
- Non-spillable Sealed Lead Acid (SLA or sometimes labelled as VRLA)
- Batteries over 9V
- Do not tape terminals of alkaline, nickel, zinc, or non-lithium button cell batteries that are 9V or less.

If you're unsure, tape all terminals with clear tape.

Does Your Kit Include Lithium Ion Batteries?

If not you may skip this section

- Double check that these are rechargeable lithium-ion batteries and not lithium metal.
- Double check that no lithium-ion battery in your kit has a cell greater than 20Wh or a total battery size greater than 100Wh. If you have larger batteries, contact LampMaster.
- If you have lithium-ion containing equipment, contact LampMaster.

ALL LITHIUM-ION BATTERIES MUST HAVE EXPOSED TERMINALS TAPED

- Use included zip-lock poly liner to help secure batteries and lessen shifting during transport.
- Attach included UN3481 and Cargo Aircraft Only labels to pail or box.
- **GROSS WEIGHT OF PACKAGE CANNOT EXCEED 66 POUNDS.**

Return Instructions

- FedEx label will be included (1/2 and 1 gal pails) or already attached (2.5 and 5 gal pails).
- Send out with your regular FedEx shipments, drop-off at a FedEx store, or request a pickup.
 - Schedule a pickup online at LampMaster.com (click 'Request FedEx Pickup' button) OR
 - Schedule a pickup by calling 1-800-GOFEDEX and say "PRP" at first voice prompt.

Nathan Keys
Program Manager